

## 400A DC/AC True RMS Watt Clamp Meter

Measure Watts, Current, and Voltage in hard to reach locations

### Features:

- True RMS AC Voltage and Current
- DC and AC True Power to 240kW
- Highest resolution of any power clamp multimeter (10W or 100mA)
- 0.9" (23mm) jaw opening
- Large 4000 count LCD display
- Fast 40 segment analog bargraph current
- Auto Zero function for DC Current
- Data Hold, Max/Min recall display
- Frequency to 1MHz
- Low battery indication
- Complete with test leads, 2 AA batteries, and carrying case



CE  **CAT II-600V**

Specifications: Range	Resolution	Accuracy $\pm$ (%rdg+digits)	Input Signal Range
AC Power: 40kW	10W	$\pm$ (1.5% + 3d)@50/60Hz	0-250V, 0-400A, PF 0-1
240kW	100W	$\pm$ (1.5% + 3d)@50/60Hz	0-600V, 0-400A, PF 0-1
DC Power: 40kW	10W	$\pm$ (1.5% + 3d)	0-250V, 0-400A
240kW	100W	$\pm$ (1.5% + 3d)	0-600V, 0-400A
AC Current: 400A	100mA	$\pm$ (1.5% + 3d)@50/60Hz	Overload protection: 600A AC (AC frequency range 40Hz-1kHz)
DC Current: 400A	100mA	$\pm$ (1.5% + 3d)	Overload protection: 600A DC
AC Voltage: 600V	1V	$\pm$ (1.5% + 2d)@50/60Hz	Overload protection: 800V AC
DC Voltage: 400V	0.1V	$\pm$ (1.0% + 2d)	Overload protection: 800V DC
Frequency: 1MHz	0.01-100Hz	$\pm$ (0.5% + 2d)	Overload protection: 600V AC
Dimensions:	7.2x2.5x1.4" (183x64x36mm)		
Weight:	6.7oz (190g including batteries)		

### Ordering Information:

- 380940** .....400A AC/DC True RMS Watt Clamp-on  
**380940-NIST**....400A AC/DC TRMS Watt Clamp-on with NIST Certificate  
**480172** .....AC Line Separator, 3-prong plug

**EXTECH INSTRUMENTS CORPORATION**  
 285 Bear Hill Road, Waltham, MA 02451-1064, U.S.A.  
 Phone: 781-890-7440 • FAX 781-890-7864

ISO 9001:2000 CERTIFIED

**"Make mine an Extech!"™**  
[www.extech.com](http://www.extech.com)



08/13/06 - R1